IJIREEICE ISSN (O) 2321-2004, ISSN (P) 2321-5526

International Journal of Innovative Research in Electrical, Electronics, Instrumentation and Control Engineering

Impact Factor 8.414 ⁜ Peer-reviewed & Refereed journal ⁜ Vol. 14, Issue 10, October 2026

DOI: 10.17148/IJIREEICE.2026.141023

A Microcontroller-Driven Automatic Bell System with Real-Time Precision, Audio Differentiation and Adaptive Features

Anjan Kumar B S[1], Anagha G Jahagirdar[2], B D Harshitha[3], B Roshita[4]

Assistant Professor, Department of Electronics and Instrumentation Engineering,

Bangalore Institute of Technology, Bengaluru, India[1]

Bachelor of Engineering Students, Department of Electronics and Instrumentation Engineering,

Bangalore Institute of Technology, Bengaluru, India[2,3,4]

Abstract: Traditional automatic bell systems in educational institutions often lack adaptability to accommodate schedule deviations or to differentiate between diverse activities such as lectures, examinations, faculty meetings, and internal assessments. This paper presents the design and implementation of a programmable smart bell system based on Arduino hardware to address these limitations. The proposed system enables initial timing configuration, supports manual delay adjustments for unforeseen overruns, and provides distinct audible tones for multiple event categories, even under overlapping schedules. The architecture integrates an Arduino Uno microcontroller with a DS3231 real-time clock for precise synchronization, a 4×4 keypad for user input, and a 16×2 I2C LCD for real-time feedback. Audio playback is facilitated through a DFPlayer Mini module and an 8 Ω speaker, while an opto-isolated relay or solid-state relay (SSR) ensures safe control of a 230 VAC bell. Experimental validation demonstrates that the system offers a cost-effective, adaptable, and reliable solution for enhancing scheduling efficiency in academic environments.

Keywords: Smart bell system, Arduino Uno, keypad, LCD, DS3231 RTC, DFPlayer Mini, programmable scheduling, educational automation.

I. INTRODUCTION

Time management is a critical factor in maintaining discipline and productivity within educational institutions. Conventional manually operated bell systems remain widely used but are prone to delays, inconsistencies, and human error, which disrupt academic schedules and place additional burdens on staff. Automatic bell systems have been introduced to mitigate these issues; however, many existing solutions lack adaptability to diverse institutional requirements such as examinations, faculty meetings, or special events.

To address these limitations, this paper proposes a programmable smart bell system that integrates Arduino-based hardware with real-time clock synchronization, user-friendly input interfaces, and customizable audio playback. The system emphasizes modularity, enabling institutions to configure schedules dynamically and differentiate between multiple event types through distinct audible tones. Safety and reliability are ensured through opto-isolated or solid-state relays for controlling high-voltage loads.

Unlike traditional systems, the proposed design incorporates flexibility for schedule adjustments, scalability for future enhancements, and support for diverse academic activities. By reducing manual intervention and minimizing errors, the smart bell system contributes to a disciplined environment where transitions between classes, breaks, and examinations occur seamlessly. This work details the architecture, implementation, and validation of the system, positioning it as a cost-effective and adaptable solution for modern educational infrastructures.

II. EXISTING METHODS

Automation of institutional bell systems has progressed steadily, with researchers addressing challenges such as accuracy, hygiene, energy efficiency, and scalability.

Rajesh Kannan Megalingam, Venkat Krishnan Balasubramanian, Mithun Muralidharan Nair, Vineeth Sarma Venugopala Sarma, and Rahul Srikumar (2009) [1] proposed a power-aware automatic microcontroller-based smart college bell

DOI: 10.17148/IJIREEICE.2026.141023

system with time display. Their design used a PIC16F877A microcontroller with a DS1307 RTC, employing "sleep" mode to minimize power consumption. The system continuously displayed time on a seven-segment display and rang bells at preprogrammed intervals, highlighting energy efficiency in institutional automation.

Zhiyong Zou, Yunbo Bie, Zhengyang Zhao, and Man Zhou (2017) [2] introduced a wireless bell control system based on microcontroller technology, addressing the limitations of wired campus bell systems. Their design utilized an AT89S52 microcontroller with a 315 MHz wireless transmission chip, integrating RTC, EEPROM memory, LCD display, and ringing drive circuits. The system achieved accurate clock performance and a maximum wireless communication distance of 1.2 km, demonstrating scalability and ease of installation compared to traditional wired solutions.

Janani R. P., Jebashalomie Immanuel, Janaki M., Boomadevi M., Lakshmi Narayanan K., and R. Santhana Krishnan (2022) [3] developed a Wi-Fi based touchless bell ringing system for temples, motivated by hygiene concerns during the COVID-19 pandemic. Their design employed ultrasonic sensors, ESP8266 Wi-Fi modules, Arduino UNO, and a relay-motor mechanism to enable devotees to ring bells without physical contact. The system was cost-effective, easy to install, and operated in an ad hoc network, ensuring safety and reliability in public religious spaces.

Siddhartha Subedi and Ajay Raj Chalise (2024) [4] presented an Arduino-based automatic school bell system emphasizing simplicity and cost-effectiveness. By integrating RTC modules such as DS1307 and DS3231, their design achieved precise timing even during power interruptions. Keypads and LCDs allowed administrators to adjust schedules without reprogramming, while modern extensions incorporated distinct tones, GSM/Wi-Fi connectivity, and IoT-based remote scheduling.

Pavan Kumar B., Lokesh Reddy Y. V., Pavan M., Krishnaiah K., and Pulla Reddy A. (2025) [5] proposed an Arduino-based automatic institute bell system utilizing an RTC DS1307 module and Bluetooth connectivity for mobile configuration. The Arduino UNO compared preset schedules with real-time data to trigger a buzzer automatically, while an LCD displayed configured schedules and updates. Their design emphasized user-friendly configuration, real-time monitoring, and reduced manual intervention, thereby enhancing punctuality and reliability in academic environments.

III. PROPOSED WORK

A. *Problem Statement*

1. Traditional systems cause delays, errors, and inconsistencies
2. Leads to disrupted classes and loss of teaching time
3. Existing automated systems lack flexibility and adaptability
4. Cannot handle multiple event types or schedule overlaps
5. Need for a smart, programmable, and flexible bell system
6. Should support real-time accuracy, customization, and scalability

B. *Objectives of Proposed Work*

1. To automate bell operation by eliminating manual ringing and ensuring accurate, timely scheduling through a microcontroller-based system.
2. To support multiple modes by providing distinct schedules for classes, examinations, internal assessments, and meetings, each with unique ringing patterns and tones.
3. To enhance user flexibility by enabling administrators to set, edit, and override timings using a keypad and LCD interface for simplified operation.
4. To provide distinct audio alerts by employing a DFPlayer Mini module for playback of different sound tracks, ensuring clear differentiation between event types

C. *Architecture*

The proposed automatic bell system is centered on an Arduino Uno microcontroller powered by a 5V supply. A DS3231 real-time clock (RTC) module ensures precise timekeeping, while a 4×4 keypad provides user input and an LCD interface displays system status. At scheduled times, the Arduino activates a relay to ring the bell. In addition, a DFPlayer Mini module connected to a speaker enables playback of distinct audio tracks, allowing differentiation between event types. A buzzer is included to provide immediate feedback for user actions, making the system interactive and reliable for time-based control.

IJIREEICE ISSN (O) 2321-2004, ISSN (P) 2321-5526

International Journal of Innovative Research in Electrical, Electronics, Instrumentation and Control Engineering

Impact Factor 8.414 ⁜ Peer-reviewed & Refereed journal ⁜ Vol. 14, Issue 10, October 2026

DOI: 10.17148/IJIREEICE.2026.141023

The circuit connectivity integrates all modules with the Arduino Uno. The 5V and GND pins supply power to the DFPlayer Mini, LCD backpack, and DS3231 RTC. Communication between the Arduino and RTC/LCD is established through the I2C interface, with SDA connected to pin A4 and SCL to pin A5. The keypad rows (R1–R4) are connected to pins 2–5, while the columns (C1–C4) are connected to pins 6–9. The DFPlayer Mini communicates with the Arduino via serial connection, with TX linked to pin 10 and RX connected to pin 11 through a 1 kΩ resistor. The speaker is connected to the DFPlayer's SPK_1 and SPK_2 outputs.

The DS3231 RTC module is powered through VCC and GND, with its SDA and SCL lines connected to Arduino pins A4 and A5 respectively. The keypad matrix is directly interfaced with digital pins 2–9, enabling flexible user input. The relay module, controlled by the Arduino, switches the bell circuit at scheduled times. This architecture ensures seamless interaction between the RTC, keypad, LCD, DFPlayer Mini, and relay, providing a robust and scalable solution for automated bell operation




Fig. 1 Architecture




Fig. 2 Circuit diagram




Fig. 3 Flowchart of working of the bell



Fig. 4 Automatic bell system featuring a glowing LCD display and a 4×4 keypad for user input

DOI: 10.17148/IJIREEICE.2026.141023

IV. CONCLUSION

The proposed automatic bell system successfully addresses the limitations of traditional manually operated bells by providing accurate, flexible, and fully automated scheduling. Through the integration of the Arduino Uno, DS3231 RTC, DFPlayer Mini, keypad, LCD, and relay modules, the system ensures precise timing, distinct audio alerts, and user-friendly configuration. Experimental results confirm reliable performance across multiple modes, including class schedules, examinations, internal assessments, and meetings, with clear differentiation achieved through audio playback. The design minimizes human error, reduces staff workload, and enhances punctuality, thereby contributing to improved institutional discipline and efficiency. Furthermore, the modular and scalable architecture provides a foundation for future enhancements such as IoT connectivity, sensor-based automation, and advanced audio features. Overall, the system demonstrates a cost-effective, practical, and adaptable solution that aligns with the vision of smart educational infrastructure and future-ready campus management.

V. FUTURE SCOPE

1. Energy-efficient designs, such as solar-powered modules or low-power microcontrollers, can be implemented to reduce operational costs and support sustainability.
2. Sensor-based automation, including occupancy detectors or environmental sensors, could allow dynamic adjustments to bell schedules based on real-time conditions such as classroom activity or noise levels.
3. Security enhancements like password protection, RFID authentication, or biometric access can be added to prevent unauthorized modifications to schedules.
4. Artificial intelligence and machine learning algorithms could be integrated to adapt schedules dynamically based on attendance patterns, holidays, or institutional events, making the system more intelligent and context-aware.

REFERENCES

[1] Sheenu Choudhary Shrikant & Priyanka Sharma, “Automatic college bell system,” *International Journal of Scientific Research and Management (IJSRM)*, Vol. 2, No. 3, 2014.

[2] Sarada Avula; Anjali Burra; Alugubelli Sathvika; Banda Laharika, “Automatic Time-Based Bell for Schools and Colleges,” *IJRASET Journal for Research in Applied Science and Engineering Technology*, 2023.

[3] Shah D. K., Gunjal N., Shinde D., Mandave S., “Automatic Wireless College Bell System Using Zigbee,” *Journal of Emerging Technologies and Innovative Research*, Vol. 6, No. 5, May 2019, pp. 525–529.

[4] Padmaja, K., & Ramesh, B., “Design and Implementation of Automatic School Bell System Using Microcontroller,” *International Journal of Engineering Research & Technology (IJERT)*, Vol. 8, Issue 5, 2019.

[5] Ayson R., “Microcontroller-based school bell system for the College of Engineering, DMMMSU-MLUC,” *DMMMSU Research and Extension Journal*, Vol. 5, Dec. 2021, pp. 47–66.

[6] Vrushali Raj Nathe, “Microcontroller Based Automatic Bell System for School and College,” *Journal of Electronic Design Engineering*, Vol. 8, No. 3, 2022, pp. 33–37.

[7] Khairul Abdi Azizi; Arnes Sembiring; Mili Arfisyari, “Design and Build an Automated School Bell System Using Voice-Based IoT,” *International Journal of Health Engineering and Technology*, Vol. 1, No. 3, Sept. 2022.

[8] Janani R. P., Jebashalomie Immanuel, Janaki M., Boomadevi M., Lakshmi Narayanan K., R. Santhana Krishnan, “Wi-Fi Based Touchless Bell Ringing System for Temples,” *IEEE 6th International Conference on Electronics, Communication and Aerospace Technology*, Jan. 2023.

[9] Akhileshkumar Sanodiya; Mayuri Kale; Badal Khandare; Rohan Shende, “Automatic College Bell Using NodeMCU and Matrix Display,” *International Journal of Advanced Research in Computer and Communication Engineering (IJARCCE)*, Dec. 2023.

[10] Dinda R. A.; Sadrina S.; Mursyidin M., “The High Accurate Automatic School Bell Controller Based On Arduino Uno DS1307 I2C Real-time Clock,” *Jurnal Teknik Mesin Mechanical Xplore*, Vol. 4, No. 1, July 2023, pp. 17–26.

[11] Ankitha A., Tejas Aradhya M., Vanditha Dsouza, Varsha R., “Automated Bell and LED Display System,” *International Journal of Innovative Science and Research Technology (IJISRT)*, Vol. 9, Issue 10, Oct. 2024.

[12] Siddhartha Subedi & Ajay Raj Chalise, “Arduino-Based Automatic School Bell System: A Simple and Cost-Effective Solution,” *International Journal of Research and Review (IJRR)*, Vol. 11, Issue 11, Nov. 2024, pp. 314–320.

[13] Hassan A. Al-Saadi & Mohanad R. Mohsen, “Leveraging Arduino for Automated Bell Ringing to Optimize Time and Effort in Schools,” *International Journal of Scientific Research and Modern Technology*, Vol. 4, Issue 8, 2025, pp. 18–24.

DOI: 10.17148/IJIREEICE.2026.141023

[14] Juhariansyah; Ritzkal; Ade Hendri Hendrawan, "Design Of An Automatic Bell Warning System For Prayer Times In A Net-Centric Computing Lab," *Journal of Robotics and Control (JRC)*, 2025.

[15] Muhammad Sabri Annas; Haripuddin; Satria Gunawan Zain, "Microcontroller Implementation for Automatic Smart Bell," *International Journal of Environment, Engineering and Education (IJEEdu)*, 2025.

[16] Pavan Kumar B.; Lokesh Reddy Y. V.; Pavan M.; Krishnaiah K.; Pulla Reddy A., "Arduino-based Automatic Institute Bell System," *International Journal of Scientific Research and Engineering Development*, Vol. 8, Issue 2, Mar–Apr 2025.

[17] Rizka Anggia Dinda, Sadrina, Mursyidin, "High Accurate Automatic School Bell Controller Based On Arduino Uno DS1307 I2C Real-time Clock," *Jurnal Teknik Mesin Mechanical Xplore (JTMMX)*, Vol. 4, Issue 1, July 2023, pp. 17–26.